

SERVICE MANUAL

STEREO AV RECEIVER

SPECIFICATIONS

FM tuner section

Tuning range	87.5 MHz to 108 MHz
Usable sensitivity	13.2 dBf
Antenna terminals	75 ohms(unbalanced)

AM tuner section

Tuning range	531 - 1,602 kHz (9 kHz step) 530 - 1,702 kHz (10 kHz step)
Usable sensitivity	350uV/m
Antenna	Loop antenna

Amplifier section

Power output	100 watts per channel, Min. RMS at 8 ohms, from 40 Hz to 20 kHz, with no more than 0.9% Total Harmonic Distortion
Total harmonic distortion	0.08%(50 W,1 kHz, 8 ohms, Front)
Input	AUDIO IN PHONO: 1.5mV, adjustable(47 k ohms) VIDEO 1/DVD/MD, VIDEO 2/LD/TV, VIDEO 3, CD, AUX: 200mV, adjustable(47 k ohms) TAPE MONITOR: 250 mV, (47 k ohms) VIDEO IN: 1 Vp-p (75 ohms)
Output	AUDIO OUT (REC OUT): 200 mV (1 kohm) VIDEO OUT (MONITOR): 1 Vp-p (75 ohms) SUB WOOFER: 2V (47 kohms) SPEAKERS IMP: 8 ohm (front speakers A and B): accepts speakers of 8 ohms or more. PHONES (stereo minijack): accepts headphones of 32 ohms or more

Muting

-20dB

General

Power requirements	120V AC, 60 Hz
Power consumption	75W
Power consumption in standby mode	ECO OFF: 17W ECO ON: 1W
Dimensions (W x H x D)	430 x 155 x 392.5 mm (17 x 6 ¹ / ₈ x 15 ¹ / ₂ in.)
Weight	9.1 kg (20 lb 1oz.)

• Design and specifications are subject to change without notice.

ACCESSORIES / PACKAGE LIST

REF. NO.	PART NO.	KANRI NO.	DESCRIPTION
1	8A-AR5-903-010		IB, U (ESF) M
2	87-006-225-010		ANT, LOOP ANT NC2
3	87-043-115-010		FEEDER-ANT, FM
4	8A-AR5-701-010		RC UNIT, RC-AAR04 BLK

ELECTRICAL MAIN PARTS LIST

REF. NO.	PART NO.	KANRI NO.	DESCRIPTION	REF. NO.	PART NO.	KANRI NO.	DESCRIPTION
IC				C112	87-012-368-080		C-CAP,S 0.1-50 Z F
	87-017-022-080		C-IC,NJM2068M-D(T1)	C113	87-016-658-090		CAP,E 4700-35 M SMG
	87-017-726-080		C-IC,BU4052BCF	C114	87-016-658-090		CAP,E 4700-35 M SMG
	87-A21-202-040		C-IC,M62445AFP	C115	87-012-368-080		C-CAP,S 0.1-50 Z F
	87-020-784-080		C-IC,TC4053BF	C116	87-012-368-080		C-CAP,S 0.1-50 Z F
	8A-AR5-601-010		C-IC,UPD780226-016-3BA				
	87-070-083-010		IC,GP1U281X	C117	87-012-368-080		C-CAP,S 0.1-50 Z F
	87-A20-820-010		IC,BA7625	C118	87-012-368-080		C-CAP,S 0.1-50 Z F
	87-017-917-080		C-IC,BU4066BCF	C119	87-A10-462-090		CAP,E 6800-63 SMG VB
				C120	87-A10-462-090		CAP,E 6800-63 SMG VB
				C121	87-010-260-080		CAP,E 47-25 M 11L SME
TRANSISTOR				C122	87-010-403-080		CAP,E 3.3-50 M 11L SME
	87-A30-197-080		TR,KTA1267GR	C123	87-010-385-080		CAP,E 220-25 M SME
	87-026-245-080		TR,DTC114ES	C124	87-010-385-080		CAP,E 220-25 M SME
	87-A30-198-080		TR,KTC3199GR	C125	87-010-247-080		CAP,E 100-50 M SME
	89-110-372-080		C-TR,2SA1037K(R)	C126	87-010-263-080		CAP,E 100-10 M 11L SME
	89-213-702-010		TR,2SB1370E				
	87-A30-083-080		TR,CSD1489B	C127	87-010-197-080		C-CAP,S 0.01-25 K B C2012
	87-A30-075-080		C-TR,2SA1235F	C143	87-A10-712-080		C-CAP,S 0.22-50 Z F
	87-A30-076-080		C-TR,2SC3052F	C144	87-A10-712-080		C-CAP,S 0.22-50 Z F
	87-026-610-080		TR,KTC3198GR	C203	87-010-176-080		C-CAP,S 680P-50 J SL
	87-026-609-080		TR,KTA1266GR	C204	87-010-176-080		C-CAP,S 680P-50 J SL
	87-A30-257-080		C-TR,2SD1306E				
	87-A30-107-070		C-TR,CMBT5401	C205	87-010-405-080		CAP,E 10-50 M 11L SME
	87-A30-190-080		TR,CC5551	C206	87-010-405-080		CAP,E 10-50 M 11L SME
	87-A30-097-010		TR,FN1016	C209	87-010-392-080		CAP,E 33-35 M 11L SME
	87-A30-098-010		TR,FP1016	C210	87-010-392-080		CAP,E 33-35 M 11L SME
	87-A30-106-070		C-TR,CMBT5551	C211	87-010-322-080		C-CAP,S 100P-50 J CH GRM
	87-A30-186-010		FET,2SK3053				
	87-A30-072-080		C-TR,RT1P 144C	C212	87-010-322-080		C-CAP,S 100P-50 J CH GRM
	87-A30-074-080		C-TR,RT1P 141C	C215	87-A10-897-080		CAP,E 100-25 BP SME
	87-026-236-080		C-TR,DTC124EK	C216	87-A10-897-080		CAP,E 100-25 BP SME
	87-026-232-080		C-TR,DTA144WK	C217	87-A10-516-080		C-CAP,S 100P-200 J CH
	87-A30-071-080		C-TR,RT1N 144C	C218	87-A10-516-080		C-CAP,S 100P-200 J CH
	87-A30-087-080		C-FET,2SK2158				
DIODE				C221	87-A10-369-080		C-CAP,S 0.47-16 K B
	87-020-465-080		DIODE,1SS133	C222	87-A10-369-080		C-CAP,S 0.47-16 K B
	87-A40-345-080		ZENER,MTZJ10C	C223	87-010-402-080		CAP,E 2.2-50 M 11L SME
	87-A40-468-080		C-DIODE,HSM2836CTR	C224	87-010-402-080		CAP,E 2.2-50 M 11L SME
	87-A40-115-060		DIODE,RS603M	C225	87-010-196-080		C-CAP,S 0.1-25 Z F C2012
	87-A40-469-080		C-DIODE,HSM2838CTR				
	87-A40-004-080		ZENER,MTZJ16A	C226	87-016-251-080		CAP,E 220-16 M SMG
	87-A40-335-080		ZENER,MTZJ11C T-72	C227	87-010-178-080		C-CAP,S 1000P-50 K B C2012
	87-A40-224-010		DIODE,GBU8DL	C228	87-010-178-080		C-CAP,S 1000P-50 K B C2012
	87-070-274-080		DIODE,1N4003 SEM	C229	87-016-251-080		CAP,E 220-16 M SMG
	87-A40-435-080		ZENER,MTZJ30D	C230	87-A10-354-080		C-CAP,S 0.047-50 K B
	87-A40-341-080		ZENER,MTZJ36A				
	87-A40-646-010		DIODE,FMB-G16L	C231	87-A10-354-080		C-CAP,S 0.047-50 K B
	87-A40-437-080		ZENER,MTZJ4.3B	C241	87-A12-314-080		CAP,CER 47P-500 J SL
	87-070-136-080		ZENER,MTZJ5.1B	C242	87-A12-314-080		CAP,CER 47P-500 J SL
	87-A40-488-080		DIODE,1SS244	C285	87-010-186-080		C-CAP,S 4700P-50 K B C2012
	87-A40-438-080		ZENER,MTZJ4.7A	C287	87-010-190-080		C-CAP,S 0.01-50 Z F C2012
	87-A40-344-080		ZENER,MTZJ6.2C				
MAIN C.B				C288	87-010-190-080		C-CAP,S 0.01-50 Z F C2012
C101	87-010-235-080		CAP,E 470-16 M SME	C289	87-010-190-080		C-CAP,S 0.01-50 Z F C2012
C102	87-010-235-080		CAP,E 470-16 M SME	C290	87-010-190-080		C-CAP,S 0.01-50 Z F C2012
C103	87-010-384-080		CAP,E 100-25 M 11L SME	C291	87-012-368-080		C-CAP,S 0.1-50 Z F
C104	87-010-382-010		CAP,E 22-25 M SME	C292	87-012-368-080		C-CAP,S 0.1-50 Z F
C105	87-010-247-080		CAP,E 100-50 M SME				
C106	87-010-384-080		CAP,E 100-25 M 11L SME	C293	87-012-368-080		C-CAP,S 0.1-50 Z F
C107	87-010-263-080		CAP,E 100-10 M 11L SME	C294	87-012-368-080		C-CAP,S 0.1-50 Z F
C108	87-012-140-080		C-CAP,S 470P-50 J CH	C295	87-012-368-080		C-CAP,S 0.1-50 Z F
C109	87-012-368-080		C-CAP,S 0.1-50 Z F	C296	87-012-368-080		C-CAP,S 0.1-50 Z F
C110	87-012-368-080		C-CAP,S 0.1-50 Z F	C297	87-012-368-080		C-CAP,S 0.1-50 Z F
C111	87-012-368-080		C-CAP,S 0.1-50 Z F				
				C298	87-012-368-080		C-CAP,S 0.1-50 Z F
				C501	87-010-404-080		CAP,E 4.7-50 M 11L SME
				C502	87-010-404-080		CAP,E 4.7-50 M 11L SME
				C503	87-012-157-080		C-CAP,S 330P-50 J CH GRM
				C504	87-012-157-080		C-CAP,S 330P-50 J CH GRM
				C511	87-010-404-080		CAP,E 4.7-50 M 11L SME
				C512	87-010-404-080		CAP,E 4.7-50 M 11L SME
				C513	87-010-260-080		CAP,E 47-25 M 11L SME
				C514	87-010-260-080		CAP,E 47-25 M 11L SME
				C515	87-010-370-080		CAP,E 330-6.3 M SME
				C516	87-010-370-080		CAP,E 330-6.3 M SME
				C517	87-010-196-080		C-CAP,S 0.1-25 Z F C2012
				C518	87-010-196-080		C-CAP,S 0.1-25 Z F C2012
				C519	87-010-196-080		C-CAP,S 0.1-25 Z F C2012
				C520	87-010-196-080		C-CAP,S 0.1-25 Z F C2012

REF. NO.	PART NO.	KANRI NO.	DESCRIPTION	REF. NO.	PART NO.	KANRI NO.	DESCRIPTION	
C531	87-010-213-080		C-CAP,S 0.015-25 K B GRM	R212	87-A00-418-010		RES,M/F 0.15-3W J	
C532	87-010-992-080		C-CAP,S 0.047-25 K B MK212	R231	87-A00-418-010		RES,M/F 0.15-3W J	
C533	87-015-785-080		C-CAP, 0.1-25 Z F C3216	R232	87-A00-418-010		RES,M/F 0.15-3W J	
C535	87-010-404-080		CAP,E 4.7-50 M 11L SME	R233	87-A00-418-010		RES,M/F 0.15-3W J	
C536	87-010-404-080		CAP,E 4.7-50 M 11L SME	R234	87-A00-418-010		RES,M/F 0.15-3W J	
C539	87-010-401-080		CAP,E 1-50 M 11L SME	R281	87-A00-373-050		RES,M/F 270-1W J VTP	
C540	87-010-401-080		CAP,E 1-50 M 11L SME	R282	87-A00-373-050		RES,M/F 270-1W J VTP	
C541	87-010-185-080		C-CAP,S 3900P-50 K B	R283	87-A00-373-050		RES,M/F 270-1W J VTP	
C542	87-010-185-080		C-CAP,S 3900P-50 K B	R284	87-A00-373-050		RES,M/F 270-1W J VTP	
C547	87-010-404-080		CAP,E 4.7-50 M 11L SME	S291	87-A90-174-010		SW,PUSH 2-2-2 R2121382ES	
C548	87-010-404-080		CAP,E 4.7-50 M 11L SME	S292	87-A90-174-010		SW,PUSH 2-2-2 R2121382ES	
C549	87-016-081-080		C-CAP,S 0.1-16 K R GRM	TH201	87-A91-081-080		C-THMS,100K-K 20P	
C550	87-016-081-080		C-CAP,S 0.1-16 K R GRM	TH202	87-A91-081-080		C-THMS,100K-K 20P	
C554	87-010-196-080		C-CAP,S 0.1-25 Z F C2012	W003	8Z-NF3-645-010		CONN ASSY,9P VH	
C555	87-010-405-080		CAP,E 10-50 M 11L SME	WH101	87-A90-510-010		HLDR,WIRE 2.5-9P	
C556	87-010-248-080		CAP,E 220-10 M 11L SME	FRONT C.B				
C557	87-010-405-080		CAP,E 10-50 M 11L SME					
C560	87-010-196-080		C-CAP,S 0.1-25 Z F C2012					
C561	87-012-140-080		C-CAP,S 470P-50 J CH		C801	87-010-322-080		C-CAP,S 100P-50 J CH GRM
C562	87-012-140-080		C-CAP,S 470P-50 J CH		C803	87-010-196-080		C-CAP,S 0.1-25 Z F C2012
					C805	87-012-141-080		C-CAP,S 0.22-16 Z F C2012
C565	87-010-404-080		CAP,E 4.7-50 M 11L SME	C806	87-010-400-040		CAP,E 0.47-50 M 11L SME	
C566	87-010-404-080		CAP,E 4.7-50 M 11L SME	C807	87-010-196-080		C-CAP,S 0.1-25 Z F C2012	
C605	87-010-405-080		CAP,E 10-50 M 11L SME					
C606	87-010-405-080		CAP,E 10-50 M 11L SME	C808	87-010-498-040		CAP,E 10-16 M 5L SRE	
C701	87-010-196-080		C-CAP,S 0.1-25 Z F C2012	C809	87-010-196-080		C-CAP,S 0.1-25 Z F C2012	
				C810	87-010-196-080		C-CAP,S 0.1-25 Z F C2012	
C702	87-010-196-080		C-CAP,S 0.1-25 Z F C2012	C811	87-A10-189-040		CAP,E 220-10 M 5L	
C745	87-012-368-080		C-CAP,S 0.1-50 Z F	C812	87-A10-189-040		CAP,E 220-10 M 5L	
C746	87-012-368-080		C-CAP,S 0.1-50 Z F					
C901	87-010-406-080		CAP,E 22-50 M 11L SME	C814	87-010-178-080		C-CAP,S 1000P-50 K B C2012	
C902	87-010-406-080		CAP,E 22-50 M 11L SME	C816	87-010-312-080		C-CAP,S 15P-50 J CH GRM	
				C817	87-012-155-080		C-CAP,S 180P-50 J CH GRM	
C903	87-010-406-080		CAP,E 22-50 M 11L SME	C818	87-010-178-080		C-CAP,S 1000P-50 K B C2012	
C904	87-010-406-080		CAP,E 22-50 M 11L SME	C819	87-012-156-080		C-CAP,S 220P-50 J CH GRM	
C905	87-010-406-080		CAP,E 22-50 M 11L SME					
C906	87-010-260-080		CAP,E 47-25 M 11L SME	C820	87-012-156-080		C-CAP,S 220P-50 J CH GRM	
C907	87-010-196-080		C-CAP,S 0.1-25 Z F C2012	C821	87-010-178-080		C-CAP,S 1000P-50 K B C2012	
				C822	87-010-182-080		C-CAP,S 2200P-50 K B C2012	
C908	87-010-387-080		CAP,E 470-25 M SME	C823	87-010-182-080		C-CAP,S 2200P-50 K B C2012	
C909	87-010-371-080		CAP,E 470-6.3 M SME	C824	87-010-182-080		C-CAP,S 2200P-50 K B C2012	
C910	87-010-371-080		CAP,E 470-6.3 M SME					
C911	87-010-371-080		CAP,E 470-6.3 M SME	C825	87-010-196-080		C-CAP,S 0.1-25 Z F C2012	
C912	87-010-196-080		C-CAP,S 0.1-25 Z F C2012	C826	87-010-405-040		CAP,E 10-50 M 11L SME	
				C827	87-010-198-080		C-CAP,S 0.022-25 K B C2012	
C913	87-010-196-080		C-CAP,S 0.1-25 Z F C2012	C829	87-012-156-080		C-CAP,S 220P-50 J CH GRM	
C914	87-010-196-080		C-CAP,S 0.1-25 Z F C2012	C831	87-A10-189-040		CAP,E 220-10 M 5L	
C920	87-016-299-080		CAP,E 10-100 M SME					
CN110	87-A60-621-010		CONN,4P V 2MM JMT	C832	87-010-196-080		C-CAP,S 0.1-25 Z F C2012	
CN201	8A-AR5-621-010		CONN ASSY,2P	C833	87-012-368-080		C-CAP,S 0.1-50 Z F	
				C834	87-012-368-080		C-CAP,S 0.1-50 Z F	
CN501	87-A60-039-010		CONN,32P V 9604S-32C	C835	87-012-368-080		C-CAP,S 0.1-50 Z F	
CN503	87-A60-056-010		CONN,12P V 9604S-12C	C836	87-012-157-080		C-CAP,S 330P-50 J CH GRM	
CN503	88-912-161-110		FF-CABLE,12P 1.25 160MM					
CN901	87-A60-619-010		CONN,2P V 2MM JMT	C837	87-012-157-080		C-CAP,S 330P-50 J CH GRM	
△ J201	87-A60-199-010		TERMINAL,SP 8P CJ-9034-07 VO	C838	87-012-157-080		C-CAP,S 330P-50 J CH GRM	
				C839	87-012-157-080		C-CAP,S 330P-50 J CH GRM	
J501	87-099-609-010		JACK,PIN 4P BLK W/O SW	C840	87-012-157-080		C-CAP,S 330P-50 J CH GRM	
J502	87-099-609-010		JACK,PIN 4P BLK W/O SW	C841	87-012-157-080		C-CAP,S 330P-50 J CH GRM	
J715	87-A60-244-010		JACK,PIN 1P BLK W/O SW					
J901	87-099-911-010		JACK,PIN 3P YEL W/O SW	C842	87-012-157-080		C-CAP,S 330P-50 J CH GRM	
J902	87-099-912-010		JACK,PIN 3P YEL W/O SW W/E	C843	87-012-157-080		C-CAP,S 330P-50 J CH GRM	
				C844	87-012-157-080		C-CAP,S 330P-50 J CH GRM	
J903	87-099-911-010		JACK,PIN 3P YEL W/O SW	C847	87-010-405-040		CAP,E 10-50 M 11L SME	
J904	87-099-911-010		JACK,PIN 3P YEL W/O SW	C848	87-010-405-040		CAP,E 10-50 M 11L SME	
J905	87-099-911-010		JACK,PIN 3P YEL W/O SW					
L291	87-003-383-010		COIL,1UH K	C849	87-012-368-080		C-CAP,S 0.1-50 Z F	
L292	87-003-383-010		COIL,1UH K	C850	87-010-408-040		CAP,E 47-50 M 11L SME	
				C855	87-010-405-040		CAP,E 10-50 M 11L SME	
L293	87-003-383-010		COIL,1UH K	C866	87-012-140-080		C-CAP,S 470P-50 J CH	
L294	87-003-383-010		COIL,1UH K	CN801	87-A60-079-010		CONN,08P H 9604S-08F	
L901	87-005-239-080		COIL,100UH K LAL03					
△ PR101	87-026-691-080		FUSE,10A 125V 251	CN801	88-908-101-110		FF-CABLE, 8P 1.25 100MM	
△ PR104	87-026-691-080		FUSE,10A 125V 251	CN802	87-A60-064-010		CONN,32P H 9604S-32F	
				CN802	8A-AR3-643-010		FF-CABLE,32P 1.25 430MM	
△ PR201	87-026-691-080		FUSE,10A 125V 251	CN805	87-A60-083-010		CONN,04P H 9604S-04F	
△ PR202	87-026-691-080		FUSE,10A 125V 251	CN805	88-904-101-110		FF-CABLE, 4P 1.25 100MM	
△ R109	87-029-060-080		RES,FUSE 33-1/4W J					
R143	87-A00-261-080		RES,M/F 0.56-1W J	FL801	8A-AR5-602-010		FL,9-BT-172GNK	
R211	87-A00-418-010		RES,M/F 0.15-3W J	L801	87-A50-434-010		COIL,CLK 4.19M(TOKO)	


REF. NO.	PART NO.	KANRI NO.	DESCRIPTION	REF. NO.	PART NO.	KANRI NO.	DESCRIPTION
LED703	87-A40-317-080		LED,SLR-342VCT31 RED	C709	87-012-195-080		C-CAP,U 100P-50CH
LED705	87-A40-317-080		LED,SLR-342VCT31 RED	C711	87-010-263-080		CAP,ELECT 100-10V
LED706	87-A40-317-080		LED,SLR-342VCT31 RED	C712	87-010-196-080		CHIP CAPACITOR,0.1-25
LED707	87-A40-317-080		LED,SLR-342VCT31 RED	C713	87-012-286-080		CAP,U 0.01-25
LED708	87-A40-317-080		LED,SLR-342VCT31 RED	C714	87-012-286-080		CAP,U 0.01-25
LED709	87-A40-317-080		LED,SLR-342VCT31 RED	C717	87-012-286-080		CAP,U 0.01-25
LED710	87-A40-317-080		LED,SLR-342VCT31 RED	C719	87-012-286-080		CAP,U 0.01-25
LED711	87-A40-317-080		LED,SLR-342VCT31 RED	C721	87-012-176-080		CAP,15P
LED712	87-A40-317-080		LED,SLR-342VCT31 RED	C722	87-012-176-080		CAP,15P
S801	87-A90-095-080		SW,TACT EVQ11G04M	C723	87-012-274-080		CHIP CAP,U 1000P-50B
S802	87-A90-095-080		SW,TACT EVQ11G04M	C725	87-012-274-080		CHIP CAP,U 1000P-50B
S806	87-A90-095-080		SW,TACT EVQ11G04M	C727	87-010-196-080		CHIP CAPACITOR,0.1-25
S807	87-A90-095-080		SW,TACT EVQ11G04M	C728	87-010-248-080		CAP,ELECT 220-10V
S809	87-A90-095-080		SW,TACT EVQ11G04M	C755	87-012-286-080		CAP,U 0.01-25
S812	87-A90-095-080		SW,TACT EVQ11G04M	C756	87-012-286-080		CAP,U 0.01-25
S813	87-A90-095-080		SW,TACT EVQ11G04M	C757	87-012-188-080		C-CAP,U 47P-50 CH
S814	87-A90-095-080		SW,TACT EVQ11G04M	C758	87-012-167-080		C-CAP,U 5P-50 CH
S816	87-A90-095-080		SW,TACT EVQ11G04M	C761	87-010-196-080		CHIP CAPACITOR,0.1-25
S817	87-A90-095-080		SW,TACT EVQ11G04M	C763	87-010-829-080		CAP,U 0.047-16
SW801	87-A91-646-010		SW,RTRY EC12E12204	C764	87-012-337-080		C-CAP,U 56P-50 CH
SW802	87-A91-647-010		SW,RTRY EC12E12504	C765	87-012-286-080		C-CAP,U 0.01-25
VOLUME C.B				C769	87-010-408-080		CAP,ELECT 47-50 M 11L
C607	87-010-178-080		C-CAP,S 1000P-50 K B C2012	C770	87-010-829-080		CAP,U 0.047-16
CN601	87-A60-083-010		CONN,04P H 9604S-04F	C771	87-010-383-080		CAP,ELECT 33-25 M 11L
S601	87-A90-095-080		SW,TACT EVQ11G04M	C772	87-010-829-080		CAP,U 0.047-16
S602	87-A90-095-080		SW,TACT EVQ11G04M	C773	87-010-196-080		CHIP CAPACITOR,0.1-25
SW601	87-A91-645-010		SW,RTRY EC12E24304NON-CLICK	C774	87-010-263-080		CAP,ELECT 100-10V
VIDEO C.B				C775	87-010-404-080		CAP,ELECT 4.7-50V
C501	87-A11-148-080		CAP,TC U 0.1-50 Z F	C776	87-012-286-080		CAP,U 0.01-25
C502	87-A11-148-080		CAP,TC U 0.1-50 Z F	C777	87-010-400-080		CAP,ELECT 0.47-50V
C503	87-010-188-080		C-CAP,S 6800P-50 K B C2012	C778	87-010-401-080		CAP,ELECT 1-50V
C504	87-010-188-080		C-CAP,S 6800P-50 K B C2012	C779	87-010-401-080		CAP,ELECT 1-50V
C507	87-A11-148-080		CAP,TC U 0.1-50 Z F	C780	87-010-196-080		CHIP CAPACITOR,0.1-25
CN604	87-099-201-010		CONN,8P H BLK 6216	C781	87-010-405-080		CAP,ELECT 10-50V
CN605	8A-AR3-652-010		CONN ASSY,2P -VIDEO 3	C782	87-010-405-080		CAP,ELECT 10-50V
FB501	87-008-372-080		FLTR,EMI BL01 RN1	C783	87-012-286-080		CAP,U 0.01-25
FB602	87-008-372-080		FLTR,EMI BL01 RN1	C784	87-012-286-080		CAP,U 0.01-25
J501	87-A60-606-010		JACK,PIN 3P R/W/Y W/O SW H	C785	87-010-805-080		CAP,S 1-16
J603	87-A60-550-010		JACK,DIA6.3 BLK ST W/SW KM	C786	87-010-805-080		CAP,S 1-16
PT C.B				C787	87-012-280-080		CAP,U 3300P-50
C001	87-010-387-080		CAP,E 470-25 M SME	C788	87-012-280-080		CAP,U 3300P-50
C002	87-010-403-080		CAP,E 3.3-50 M 11L SME	C789	87-012-275-080		C-CAP,U 1200P-50 B
C003	87-A11-148-080		CAP,TC U 0.1-50 Z F	C790	87-012-275-080		C-CAP,U 1200P-50 B
C004	87-A11-148-080		CAP,TC U 0.1-50 Z F	C791	87-010-405-080		CAP,ELECT 10-50V
C005	87-A11-148-080		CAP,TC U 0.1-50 Z F	C793	87-012-273-080		C-CAP,U 820P-50 B
△ C007	87-A10-922-090		CAP,CER 0.01-250 M F KH	C794	87-010-406-080		CAP,ELECT 22-50
△ CN101	88-805-042-690		CONN ASSY,4P	C795	87-010-194-080		C-CAP,S 0.047-25 FZ
△ CN103	87-A61-057-010		CONN,9P V THL-P09P-A1	C796	87-010-403-080		CAP,ELECT 3.3-50V
△ F101	87-035-493-010		FUSE,8A 125V T 237	C797	87-012-278-080		CAP,U 2200P-50
△ FC101	87-A90-160-080		FUSE CLAMP,FC 51F	C798	87-012-278-080		CAP,U 2200P-50
△ FC102	87-A90-160-080		FUSE CLAMP,FC 51F	C799	87-010-829-080		CAP,U 0.047-16
△ PR001	87-A91-276-080		FUSE,125MA 125V F 251	C812	87-012-286-080		CAP,U 0.01-25
△ PR105	87-026-691-080		FUSE,10A 125V 251	C813	87-010-196-080		CHIP CAPACITOR,0.1-25
△ PR106	87-026-691-080		FUSE,10A 125V 251	C814	87-012-286-080		CAP,U 0.01-25
△ PT002	8Z-NF8-661-010		PT,SUB ZNF-8(U)	C819	87-010-197-080		CAP,CHIP 0.01 DM
△ PT101	8Z-AR4-601-010		PT,ZAR-4(U)	C820	87-010-260-080		CAP,ELECT 47-25V
△ RY001	87-A90-977-010		RELAY,AC12V DG12D1-O(M)	C821	87-012-286-080		CAP,U 0.01-25
△ T001	87-A60-317-010		TERMINAL, 1P MSC	C822	87-012-286-080		CAP,U 0.01-25
△ T002	87-A60-317-010		TERMINAL, 1P MSC	C823	87-012-286-080		CAP,U 0.01-25
TUNER C.B				C828	87-010-196-080		CHIP CAPACITOR,0.1-25
C701	87-010-260-080		CAP,E 47-25V	C829	87-010-196-080		CHIP CAPACITOR,0.1-25
C702	87-010-404-080		CAP,E 4.7-50V	C959	87-010-196-080		CHIP CAPACITOR,0.1-25
C703	87-012-286-080		CAP,U 0.01-25	C960	87-010-196-080		CHIP CAPACITOR,0.1-25
C704	87-012-286-080		CAP,U 0.01-25	C961	87-012-170-080		C-CAP,U 8P-50 CH
				CF801	87-008-261-080		FILTER,SFE 10.7MA5-A
				CF802	87-008-261-080		FILTER,SFE 10.7MA5-A
				CF801	87-008-261-080		FILTER,SFE 10.7MA5-A
				CN601	87-099-028-010		CONN,11P 6216 H
				FFE801	A8-8ZA-190-030		8ZA-1 FEUNM
				J801	87-A60-657-010		TERMINAL,4P HSP-154V5-02

REF. NO.	PART NO.	KANRI NO.	DESCRIPTION
L771	87-A50-266-010		COIL, FM DET-2N(TOK)
L772	87-A90-733-010		FLTR, PCFAZH-450
L781	87-005-847-080		COIL, 2.2UH (CECS)
L791	87-A50-209-010		COIL, 1 POLE MPX (MIT)
L792	87-A50-209-010		COIL, 1 POLE MPX (MIT)
L832	87-005-847-080		COIL, 2.2UH (CECS)
L981	87-NF4-650-010		COIL, AM PACK4N (TOK)
X721	87-A70-061-010		VIB, XTAL 4.500MHZ CSA-309


○チップ抵抗部品コード／CHIP RESISTOR PART CODE

チップ抵抗部品コードの成り立ち

Chip Resistor Part Coding



チップ抵抗
Chip resistor

容量 Wattage	種類 Type	許容誤差 Tolerance	記号 Symbol	寸法／Dimensions (mm)				抵抗コード : A Resistor Code : A
				外形／Form	L	W	t	
1/16W	1005	± 5%	CJ		1.0	0.5	0.35	104
1/16W	1608	± 5%	CJ		1.6	0.8	0.45	108
1/10W	2125	± 5%	CJ		2	1.25	0.45	118
1/8W	3216	± 5%	CJ		3.2	1.6	0.55	128

TRANSISTOR ILLUSTRATION



E C B

CC5551
KTA1266
KTC3198




B C E

2SB1370
FN1016
FP1016



E C B

DTC114ES
KTC3199
KTA1267




2SA1037
2SA1235
2SC3052
2SD1306
CMBT5401
CMBT5551

DTA144WK
DTC124EK
RT1N144C
RT1P141C
RT1P144C



G D S

2SK3053




2SK2158




E C B

CSD1489


WIRING-1 (MAIN)




SCHEMATIC DIAGRAM – 1 (MAIN : 1 / 2)




SCHEMATIC DIAGRAM – 2 (MAIN : 2 / 2)




WIRING-2 (FRONT)






SCHEMATIC DIAGRAM – 3 (FRONT)







SCHEMATIC DIAGRAM – 4 (VOLUME / VIDEO)











SCHEMATIC DIAGRAM – 6 (TUNER)





MECHANICAL PARTS LIST 1 / 1

REF. NO.	PART NO.	KANRI NO.	DESCRIPTION	REF. NO.	PART NO.	KANRI NO.	DESCRIPTION
1	8A-AR3-006-010		KNOB, RTRY JOG	△ 26	8Z-AR4-601-010		PT, ZAR-4 (U)
2	8A-AR5-003-010		PANEL, FR U	27	87-085-189-010		BUSHING, CORD (U)
3	8A-AR5-007-010		KEY, ASSY, ENTER	△ 28	87-A80-110-010		AC CORD ASSY, U SPT-2W
4	8A-AR5-005-010		KEY, ASSY, DOLBY	29	8A-AR5-206-010		HLDR, HT-SINK L
5	8A-AR5-006-010		WINDOW, DISP U	30	8A-AR3-011-010		BTN, SP
6	8A-AR3-045-010		KNOB, RTRY VOL	31	88-AR1-203-010		HLDR, TU
7	8A-AR3-007-010		RING, VOL	32	8A-AR5-002-010		PANEL, REAR UBM
8	8A-AR3-047-010		RING, FUN	33	87-033-209-010		TERMINAL, EARTH
9	8A-AR3-009-010		REFLECTOR, FUN	A	87-067-703-010		TAPPING SCREW, BVT2+3-10
10	87-CE3-023-010		BADGE, AIWA 30N SILV	B	87-591-095-410		TAPPING SCREW, QIT+3-8 (GLD)
11	8Z-AR1-020-110		RING, FOOT SIL	C	87-067-633-010		TAPPING SCREW, BVT2+3-8
12	8A-AR5-001-010		CABI, FR U	D	87-067-581-010		TAPPING SCREW, BVT2+3-15
13	8A-AR3-024-010		KEY, BAL	E	87-067-632-010		TAPPING SCREW, BVT2+3-15
14	8A-AR3-020-010		KEY, ECO	F	87-067-585-010		TAPPING SCREW, BVT+4-6
15	88-912-161-110		FF-CABLE, 12P 1.25 160MM	G	87-067-579-010		TAPPING SCREW, BVT2+3-8
16	8A-AR3-021-010		KEY, POWER	H	87-067-641-010		UTT2+3-8 (W/O SLOT) BL
17	8A-AR5-602-010		FL, 9-BT-172GNK R	I	87-067-584-010		TAPPING SCREW, BVT2+3-6
18	88-AR1-209-010		GUIDE, FL	J	87-067-689-010		TAPPING SCREW, BVT+3-8
19	88-904-101-110		FF-CABLE, 4P 1.25 100MM	K	87-078-191-010		S-SCREW, IT+4-10
20	8A-AR3-643-010		FF-CABLE, 32P 1.25 430MM	L	87-721-095-410		QT2+3-8GLD W/O SLOT
21	88-908-101-110		FF-CABLE, 8P 1.25 10MM				
22	8A-AR5-004-010		CABI, STEEL				
23	8Z-NB8-240-010		COVER, PL				
24	8Z-AR1-021-110		FOOT, REAR				
25	88-AR1-218-010		HLDR, PWB H8.9				

COLOR NAME TABLE

Basic color symbol	Color	Basic color symbol	Color	Basic color symbol	Color
B	Black	C	Cream	D	Orange
G	Green	H	Gray	L	Blue
LT	Transparent Blue	N	Gold	P	Pink
R	Red	S	Silver	ST	Titan Silver
T	Brown	V	Violet	W	White
WT	Transparent White	Y	Yellow	YT	Transparent Yellow
LM	Metallic Blue	LL	Light Blue	GT	Transparent Green
LD	Dark Blue	DT	Transparent Orange	GM	Metallic Green
YM	Metallic Yellow	DM	Metallic Orange		

アイワ株式会社 〒110-8710 東京都台東区池之端1-2-11 ☎03(3827)3111 (代表)
AIWA CO.,LTD. 2-11, IKENOHATA 1-CHOME, TAITO-KU, TOKYO 110, JAPAN TEL:03 (3827) 3111